



Monarch Portable Ceiling Hoist



Owner's Manual

(To Be Retained by Owner After Installation)

IMPORTANT

Be sure to read this entire manual before using the Monarch Portable Ceiling Hoist. The information in this manual is important for the safety of the user being transferred and the operator, and for the proper use and maintenance of the hoist. Transfer always presents a potential risk and this manual provides important safety information that must be read and understood to help prevent injuries.

Unauthorised modifications to this hoist may affect its safety. OpeMed (Europe) Ltd will NOT be held responsible for any accidents, incidents or performance deficiencies that occur due to any unauthorised modification to this hoist. To avoid potential injury due to the use of inadequate parts, always use only OpeMed replacement parts.

Regularly scheduled maintenance must be performed on your Monarch Portable hoist by an Authorised OpeMed Dealer to ensure safety and proper operation of the hoist. Refer to the *Maintenance* section in this manual.

Legal Manufacturer:

Savaria Concord Lifts, Inc.
2 Walker Drive
Brampton, Ontario L6T 5E1
Canada

European Representative:

OpeMed (Europe) Ltd.
Clockhouse, Dogflud Way
Farnham, Surrey, GU9 7UD

Copyright © 2016 Savaria Concord Lifts, Inc.
& OpeMed (Europe) Ltd. All rights reserved.

Printed in United Kingdom and Canada

STANDARD NOTATIONS

The following notations may be used throughout this manual to emphasise important safety information, mechanical concerns, and other important information. Please review and follow all of these messages.



DANGER

Danger messages indicate an imminently hazardous situation, which, if not avoided, results in death or serious injury. All danger messages feature a standard ISO safety alert symbol followed by the signal word **DANGER** in capitalised black lettering on a red background.



WARNING

Warning messages indicate a potentially hazardous situation, which, if not avoided, could result in death or serious injury. All warning messages feature a standard ISO safety alert symbol followed by the signal word **WARNING** in capitalised black lettering on a dark yellow background.



CAUTION

Caution messages indicate a potentially hazardous situation, which, if not avoided, could result in minor injuries. All caution messages feature a standard ISO safety alert symbol followed by the signal word **CAUTION** in capitalised black lettering on a yellow background.

NOTE

Note messages provide information, such as reminders, general information about a previous statement, or additional guidelines that do not fit into the flow of the preceding text. All note messages include the signal word **NOTE** in capitalised white lettering on a blue background.

CONTENTS

1. OVERVIEW	5
Intended Use	5
Product Life	5
Using This Manual	5
2. SAFETY INSTRUCTIONS	6
To Ensure Safety	6
Battery and Charger Safety	7
Fire and Explosion Prevention	7
Shock Prevention	8
3. DESCRIPTION	9
Exterior Views	9
hoist Controls and Connectors	10
Hand Control	10
Charger	10
Slings	11
Symbols	12
4. SPECIFICATIONS	15
Dimensions	16
5. USING THE hoist	17
Before Transfer	17
Transferring the user	17
Emergency Lowering	27
Emergency Brake	28
Charging the Battery	29
6. MAINTENANCE	30
Operator Maintenance Schedule	31
Dealer Maintenance Schedule	32
Inspection and Cleaning	33
7. TROUBLESHOOTING	34
8. ELECTROMAGNETIC COMPATIBILITY	35
Electromagnetic Compliance	35
Electromagnetic Immunity	36

1. OVERVIEW

Intended Use

The Monarch Portable Ceiling Hoist is designed for use by caregivers and health care professionals to hoist and transfer a user in a homecare, assisted-living or hospital environment. Transfer must be performed by a qualified operator as described in this manual. **Do NOT use the hoist for any other purpose.**

Product Life

The hoist is designed for a useful life of 10 years after which time it must be replaced. To ensure this life span, you must perform the preventive maintenance as specified in the *Maintenance* section in this manual.



WARNING

OpeMed (Europe) Ltd cannot ensure complete safety for a portable ceiling lift that has exceeded its useful life. Wear may cause failure of a part and lead to a patient fall.

The expected life for other parts such as slings, batteries, fuses, straps, and cords is dependent upon the proper care and use of the individual items. The items must be maintained as described in their accompanying documentation and in the *Maintenance* section in this manual.

Using This Manual

To ensure safe operation of the hoist, read this entire manual carefully, especially the *Safety Instructions*, before installing, using or maintaining the hoist. Failure to comply with all WARNINGS in this manual may result in injury. If there is anything you don't understand, contact your Authorised OpeMed Dealer for further details.

Keep this manual with the hoist and ensure all operators are fully trained in the use of the hoist as described in this manual.

2. SAFETY INSTRUCTIONS

Keep these *Safety Instructions* with the hoist at all times. Read this entire manual before installing, using or maintaining the hoist.



WARNING

Do NOT use the hoist for any purpose other than to transfer a user. To ensure safety of the user being transferred and the operator, follow all Safety Instructions.

Take the necessary precautions to avoid any risk of entanglement posed by the lifting strap or hand control cable.

To Ensure Safety

- The hoist has a safe working load of 200 kg (440 lb) or 130 kg (286 lb). Do NOT exceed this load. Refer to the nameplate tag for the Maximum Load allowed.
- The hoist must be installed by an Authorised OpeMed Dealer.
- Ensure the hoist is used only with a OpeMed ceiling track system. If the track system is not from OpeMed ensure the track system is properly assessed by a competent authority for fit, function, and safety.
- The track system must be installed by a trained and Authorised OpeMed Dealer.
- Operators must be fully trained before using the hoist.
- Ensure the sling is intended for use with this hoist and can handle the weight of the user. Ensure the sling is not damaged in any way and the sling straps are in good condition and attached properly.
- Check with a qualified health professional to ensure the user to be transferred has been deemed suitable for transfer.
- Take extra care with a user who is connected to electrodes, catheters or other medical devices to ensure safe transfer.
- Take care to avoid impact during transfer.
- Keep all components of the hoist clean and dry.
- Follow the lifting procedures provided in this manual.
- Perform the "Before each use" checks and actions specified in the *Operator Maintenance Schedule* before using the hoist.
- Ensure all checks and actions are performed at the frequency indicated in the *Maintenance* section in this manual.

Battery and Charger Safety



Contact your Authorised OpeMed Dealer if you are unsure of any of the safety instructions provided below.

- Do NOT expose the battery or charger to water or any other liquid.
- To avoid injury, do NOT alter the battery in any way. Stop using the battery if any damage is noted.
- Do NOT charge the battery in an unventilated area and do not cover the charger.
- If the battery case cracks and the contents of the battery contact your skin or clothing, rinse immediately with plenty of water.
- If the contents of the battery contact your eyes, rinse immediately with plenty of water and seek medical attention.
- Inhalation of the contents of the battery can cause respiratory irritation. Provide fresh air and seek medical attention.
- For recycling or disposal of batteries, follow the rules according to the WEEE directive (Waste of Electronic and Electrical Equipment) as well as all local laws and regulations. If you do not follow these rules, the battery may explode, leak and cause personal injury.

Fire and Explosion Prevention

- Use only lithium ion batteries that are designed for use with the hoist.
- Use only the charger that is supplied with the hoist.
- Do NOT store batteries in an area with a temperature higher than 70 degrees C (158 degrees F).
- Do NOT store the battery in direct sunlight or near any heat source.
- Do NOT expose the battery or charger to flames.
- Do NOT use the charger in the presence of any flammable anaesthetic gases.
- Do NOT short circuit the battery terminals.
- Do NOT incinerate the battery.
- Do NOT puncture the battery or try to open/dismantle the battery pack

Shock Prevention

- Do NOT touch or use the hoist if you notice any exposed or damaged wires.
- Do NOT expose electrical parts of the hoist to water or moisture.
- Do NOT attempt to use the charger in an area that has a different voltage and frequency requirement other than that specified on the nameplate.
- Do NOT attempt any repairs to the hoist, battery or charger. Always contact your Authorised OpeMed Dealer for service.

3. DESCRIPTION


Exterior Views

Figure 1



Hoist Controls and Connectors

Figure 2



Hand Control

The hand control unit can be used to operate the portable ceiling hoist. Use the UP and DOWN buttons to raise and lower the hoist.

Figure 3



Plug the hand control cable into the connector at the front of the unit and secure it with the cable clamp and screw using a Phillips screwdriver.

Charger

The portable ceiling hoist is equipped with a battery charger as shown below. Note that depending on the geographic location, the power cord provided may differ from the one shown here.

Figure 4





LED Description

Solid green: power on but not charging.
Solid yellow: charging batteries.

Slings

The following chart illustrates the different types of slings. Note that each model is offered in various sizes, and comes in mesh or solid material.

NOTE: We recommend slings are replaced 5 years after manufacture date specified on the sling label.











<p>Universal with adjustable head support</p>	
<p>Hygienic</p>	









Guidelines to Select Proper Sling Size




Size	Height	Weight
Small (S)	<5 ft	< 125 lb
Medium (M)	5 to 6 ft	125 to 250 lb
Large (L)	6 to 7 ft	250 - 440 lb

Symbols

The following chart illustrates what symbols may be used on the nameplate, the packaging and the hoist.

Symbols on nameplate	
	<p>Indicates the medical device manufacturer. This symbol is accompanied by the address of the manufacturer and the date of the manufacture.</p> <p>YYYY: Represents the year MM: Represents the month</p>
	<p>Indicates the authorised representative in the European Community.</p> <p>This symbol is accompanied by the address of the authorised representative.</p>
	<p>Indicates the manufacturer's catalogue number</p>
	<p>Indicates the manufacturer's serial number</p>
	<p>Keep dry</p>
	<p>Indicates the product complies with the medical device directive 93/42/EEC</p>
	<p>Indicates the product was certified by third-party "QPS"</p>
	<p>Indicates the product comply to the directive 2011/65/EC (RoHS)</p>
	<p>Indicates "separate collection" for all batteries and accumulators per the WEEE directive</p>
	<p>Direct current</p>

	Caution
	Refer to instruction manual/booklet
	Type BF protection against electrical shocks
MAX . LOAD :	Refers to the greatest permissible load that can be applied to the product
IPX₁X₂	Ingress Protection: X ₁ : Protection level against ingress of solid particles X ₂ : Protection level against ingress of liquids
Symbols on box label	
	Indicates the temperature limits to which the medical device can be safely exposed
	Indicates the range of humidity to which the medical device can be safely exposed
	Indicates the range of atmospheric pressure to which the medical device can be safely exposed
Symbols on hoist	
	Indicates the "Stop" button on the product
	Indicates low battery level when the green light flashes


	Indicates heat warning when the yellow light turns on solid
	Indicates the location of the emergency lowering system on the product
	Indicates the location of the battery charger connection on the product

4. SPECIFICATIONS

Product	
Product Weight	5 kg (11 lb)
Product Life	10 years
Safe Working Load (SWL)	200 kg (440 lb) or 130 kg (286 lb)
Lifting Speed	5.5 cm/sec (2.2 in/sec) at 0 kg 5 cm/sec (2 in/sec) at 130 kg (286 lb) 4.5 cm/sec (1.8 in/sec) at 200 kg (440 lb)
Water Ingress Protection Rating of hoist	IP21
Noise Level	Maximum 54 dBA
Medical Electrical Equipment Class	Class 1
Protection Class	Type BF
Battery	
Battery Type	Lithium ion, 25.2V 2500 mAh
Battery Capacity	Approximately 30 cycles of 61 cm (24 in) at 200 kg (440 lb) Approximately 70 cycles of 61 cm (24 in) at 130 kg (286 lb)
Battery Charging	Full capacity in approximately 2 hours
Battery Charging Temperature	10° to 40° C (50° to 104° F)
Charger	
Charger Input	100-240 VAC, 50-60Hz
Charger Output	29.4 VDC, max 1A
Environmental Conditions	
Operating Temperature	5 °C to 40 °C (41 °F to 104 °F)
Operating Humidity	15 to 93%, non-condensing
Storage Temperature	-25 °C to 70 °C (-13 °F to 158 °F)
Storage Humidity	0 to 93%, non-condensing
Atmospheric Pressure	70 kPa to 106 kPa
WARNING: This equipment is not suitable in the presence of flammable anesthetic mixtures with air or oxygen, or with nitrous oxide.	
Controls	
Hoist Controls	UP and DOWN buttons to raise and lower the hoist

Hand Control	UP and DOWN buttons to raise and lower the hoist
Hand Control Operating Force	4 - 4.5N
Water Ingress Protection Rating of Hand Control	IP67
On/Off Power Switch	Used to shut off power to the hoist and as an emergency stop feature
Certification	
IEC 60601-1:2005 A1:2012 (Medical Electrical Equipment)	
IEC 60601-1-11:2015 (Homecare)	
ISO 10535:2006 (Patient Hoist)	
CAN/CSA Z10535.1:15 (Patient Hoist)	
Compliance	
CE Marking per 93/42/EEC (Medical Device)	
2006/42/EC (Machinery Directive)	
2011/65/EU (ROHS - 100% of components)	
2002/96/EC (WEEE)	

Dimensions



5. USING THE HOIST



WARNING

Read the *Safety Instructions* in this manual **BEFORE** using the hoist.

The hoist must NEVER be operated by the user being transferred. In the unlikely case of failure, the patient could get stuck in the unit.

Before Transfer

- Ensure the hoist battery is charged.
- Ensure the track end stops are securely in place as shown below.

Figure 5



- Plug the hand control cable into the hoist. This step is optional as there are touchpad membranes near both hooks.
- Inform the user to be transferred what you are about to do.
- Always evaluate the user's general condition before transfer.
- Ensure you have a sling that is the correct size for the user. Use only slings that are designed for use with the hoist.

Transferring the Person

- 1 Place the user to be transferred into the sling as described on the following pages or per the documentation provided with the sling.
- 2 Turn on the power switch on the hoist.

NOTE

Note that the On/Off power switch can also be used as an Emergency Stop by turning the switch to the Off position.





**Do NOT move the hoist by pulling the hand control.
The handset may spring return and cause injuries.**

- 3** Unwind the hoist strap by pressing the DOWN button on the hand control while, maintaining tension on the strap with your other hand. Note that there must be tension on the hoist strap for the hoist to function.
- 4** Slide the carabiner hook into the loop of the hoist strap and then attach the carabiner hook to the trolley in the track.

Figure 6




5 Move the hoist over the user to be transferred.

6 Press the DOWN button on the hand control to lower the hoist below the chin. You need to unfold the slings straps before attaching them to the support hooks.

Please note: There are different loops on the sling straps to allow transfer from the sitting or reclined position.

- To transfer to/from the fully seated position (shown below), use the third loop at the back and the first loop at the front.
- To transfer to/from the fully reclined position (shown below), use the first loop at the back and the third loop at the front.
- Note: The second loops are used for intermediate positions.


Figure 7



Fully seated position



Fully reclined position




- 7 The universal sling has a head support system consisting of two adjustable straps. Tighten the straps as needed for full head support and release them for less support as shown below.

Figure 8



Straps tightened (full support)



Straps released

- 9 If using a sling with an aperture, install the sling on the chest near the underarm,

to maximise comfort and stability during transfer (see the photo below). The second photo below illustrates the position for transfer using a sling with an aperture.

Figure 10




Installing a sling
with an aperture



Position for transfer
using a sling with
an aperture

- 10** Note that the safety latches are spring-loaded and will close automatically.
- 11** Lift up on the safety latch with one hand and slide the sling strap onto the support hook with your other hand. The safety latch will spring closed trapping the sling strap inside the support hook. **The safety latch must be completely closed as shown below.**

Figure 11



Do NOT attempt a transfer if the support hook safety latches are not completely closed. The sling strap MUST be trapped inside the support hook to prevent the user from falling and sustaining possible injuries.

-
- 12** Before lifting the user, ensure the sling straps are securely locked in the support hooks and the user is comfortable. Make sure the sling is not caught on any obstruction.




NEVER leave a user unattended during a transfer to prevent the user from falling and sustaining possible injuries.

- 13** To hoist the user, press the UP button on the hand control or the touchpad membranes.
- 14** Lift the user until the sling clears the arms of the wheelchair, or the top of the bed, before moving the user. Guide their legs past any obstacles. Note that there is no need to raise the user in the air far above any obstacles, just far enough to clear them.
- 15** When the user is above the desired point of transfer, press the DOWN button on the hand control to lower the user.

- 16** Once the user is properly seated, loosen the straps and disengage the sling from the hoist. To do this, hoist up on the safety latch with the sling strap (as shown below) and slide the strap off.

Figure 13



- 17** Slide the hoist away from the user. Unhook the hoist from the trolley and use the hand control or touchpad membranes to shorten the strap. You can now remove the sling from around the user who was transferred.

- 18** Turn off the power switch on the hoist.

- 19** Plug the battery charger into the hoist to ensure the battery is charged for the next use.

**WARNING**

Use ONLY the charger #M920001 provided with the hoist. Using any other charger may result in permanent damage to the batteries or cause fire, explosion, or injuries.

Emergency Lowering




Use the emergency lowering feature for emergency only.

The hoist is equipped with an emergency lowering device that allows you to lower the hoist if the electrical system is not functioning. The emergency lowering device is activated using a standard 6mm Allen key (supplied with the hoist).

- 1 Turn off the power switch on the hoist.
- 2 Move the user in the hoist over the wheelchair or bed.
- 3 Using the Allen key, puncture the label to access the emergency lowering mechanism.
- 4 Turn as indicated on the punctured label to lower the user. Note that each turn of the key will lower the user slightly. Once the user is lowered safely into the wheelchair or bed, remove the Allen key from the access opening.
- 5 Call your Authorised OpeMed Dealer to service the hoist.

Figure 14



Emergency Brake

The emergency safety brake is an additional safety feature that automatically prevents the user from falling in the event of a transmission or motor failure.



WARNING

If the emergency brake has activated, do NOT attempt to unlock the brake or press the UP button as this may disengage the brake and cause the user in the hoist to fall. Do NOT attempt to use the emergency lowering device either as injuries could occur.

Contact your Authorised OpeMed Dealer to arrange for the unit to be replaced.

Charging the Battery

NOTE

If the battery charge is low, you will hear a beeping sound and see a blinking green LED on the hoist when pressing a button. The beeping sound and blinking LED will stop when the button is released. Charge the battery as soon as possible.



WARNING

Use ONLY the charger #M920001 provided with the hoist. Using any other charger may result in permanent damage to the batteries or cause fire, explosion, or injuries.

Do NOT operate the battery charger with a damaged cord or damaged charger enclosure as this may cause fire or electrical shock.

- 1 Plug the charger into the AC wall outlet. The green indicator on the charger will come on solid.
- 2 Plug the other end of the charger cord into the hoist.
- 3 The charging indicator on the charger is solid yellow when the battery is charging and solid green when the battery is fully charged.
- 4 If the battery is low, it will take approximately 2 hours for a full charge. Charge the battery fully before using the hoist again.

Plug the charger into the hoist when the hoist is not in use to ensure it is fully charged for the next use. The hoist can be charged for an extended period of time without damaging either the charger or the battery.

When you need to use the hoist again, be sure to unplug the charger before using.

The hoist should not remain stored for long periods of time without charging the battery. Charge the battery at least every month to maximise the life span.

6. MAINTENANCE

The ceiling hoist is subject to wear and tear from use. You must perform the checks and actions in the following tables to ensure safety and proper operation.



WARNING

Contact your Authorised OpeMed Dealer to perform the Dealer Checks/Actions. Safety-related maintenance and service must be performed by an Authorised OpeMed Dealer.

This maintenance schedules provides the minimum recommendations. In some cases, more frequent checks may be required per local regulations and codes.

To ensure safety of the user being transferred and the operator, do NOT use the equipment if a fault is found or if these regular checks have not been performed.

Operator Maintenance Schedule

Perform the following checks/actions as indicated. If any of the checks fail, contact your Authorised OpeMed Dealer for service or replacement of parts.

Operator Check/Action	Frequency
Charge the battery	Before every use
Check the hoist strap for wear	Before every use
Check the sling material and straps for wear	Before every use
Check for any defects or loose threads in the stitched areas of the sling	Before every use
Check the carabiner for any damage	Before every use
Check the operation of the hoist control buttons	Before every use
Check the operation of the hand control buttons	Before every use
Check the track and hardware for any damage	Before every use
Ensure the track end stops are securely in place	Before every use
Ensure the hoist moves freely along the track	Before every use
Clean the hoist casing	As required
Clean the track	Every 4 months
Check the emergency stop function (turning the power switch Off functions as the emergency stop)	Every 4 months
Check the hoist casing for any damage	Every year
Check the support hooks, carabiner and hoist strap for any damage	Every year
Check the track, hardware, and trolley wheels for damage	Every year

Dealer Maintenance Schedule

Perform the checks/actions listed in the Operator Maintenance Schedule as well as those listed in the table below.

Dealer Check/Action	Frequency
Check the hoist casing for any damage	Every year
Check the hoist transmission	Every year
Check the hoist connecting joints	Every year
Check that the emergency brake is turning freely	Every year
Check that all emergency devices are working properly	Every year
Perform a load test on the hoist and track system with the Safe Working Load	Every year
Replace the hoist strap	Every 2 years
Lubricate the roller and spool shaft	Every 2 years
Lubricate the transmission spool gear	Every 2 years



To avoid potential injury, use ONLY OpeMed parts when replacing parts.

To prevent the user from falling (or objects from falling) that may cause injuries to the user, the operator or other persons, always reinstall the track end stops if they were removed for servicing. Note that the recommended tightening torque is 20 N-m (15 lb-ft).

Figure 15



Inspection and Cleaning

To clean the Monarch Ceiling Hoist, wipe down the casing with a damp cloth using warm water and a cleaner. You can also use wipes that have a 70% v/v solution of isopropyl alcohol.

Do not use phenol, chlorine or any other type of solvent that may damage the finish.

Rub the hoist vigorously with the cloth or wipe to ensure thorough cleaning of the entire surface.



CAUTION

Do not splash, drench or immerse the unit in water as the unit could malfunction causing injuries to occur.

To ensure a better rolling surface for the trolley wheels, clean the inside of the track every 4 months. To do this, insert a damp cloth in the opening and slide it from one end of the track to the other.

7. TROUBLESHOOTING



WARNING

Do NOT open the hoist casing. Only an Authorised OpeMed Dealer is qualified to open it. Modifications made to the hoist by someone other than a qualified technician may cause serious injury.

Problem	Action
The unit starts and stops repeatedly.	If the load is greater than the Safe Working Load of the hoist, it will not function due to an overload on the motor.
The hoist emits a beeping sound during use. The unit may stop lifting the user but can still lower the user.	The battery is low and needs to be charged.
Charging indicator on the charger (yellow) does not light up when the charger is connected to the hoist.	<p>Ensure the charger is plugged into a standard electrical outlet and that the outlet has power. The green LED on the charger will be turned on.</p> <p>Note that the battery may have sufficient power and does not need recharging. The charger automatically detects if charging is required or not.</p>
The hoist does not move when you press a button on the hoist or on the hand control.	<p>Make sure the On/Off power switch on the hoist is turned On.</p> <p>Check that the battery is charged.</p> <p>Ensure the hand control is properly plugged into the hoist socket.</p> <p>Ensure the charger is not plugged into the hoist. The hoist does not allow charging and lifting at the same time.</p> <p>If the problem persists and the hoist still does operate, contact your Authorised OpeMed Dealer for service.</p>

8. ELECTROMAGNETIC COMPATIBILITY

Electromagnetic Compliance

The ceiling hoist has been tested for compliance with current regulatory standards in regards to EMI (electromagnetic interference).



WARNING

Use of this equipment adjacent to or stacked with other equipment should be avoided because it could result in improper operation. If such use is necessary, this equipment and the other equipment should be observed to verify that they are operating normally.

Use of accessories and cables other than those specified or provided by the manufacturer of this equipment, could result in increased electromagnetic emissions or decreased electromagnetic immunity of this equipment, and result in improper operation.


Portable RF communications equipment (including peripherals such as antenna cables and external antennas) should be used no closer than 30 cm (12 inches) to any part of the Monarch, including cables specified by the manufacturer. Otherwise, degradation of the performance of this equipment could result.

Guidance and Manufacturer's Declaration - Electromagnetic Emissions - For All Equipment and Systems		
The Monarch Ceiling hoist is intended for use in the electromagnetic environment specified below.		
Emissions test	Compliance	Electromagnetic environment - guidance
RF emissions CISPR 11	Group 1	The ceiling hoist uses RF energy only for its internal function. Therefore, its RF emissions are very low and are not likely to cause any interference with nearby equipment.
RF emissions CISPR 11	Class B	The ceiling hoist is suitable for use in all establishments, including domestic establishments and those directly connected to the public low-voltage power supply network supplying buildings used for domestic purposes.
Harmonic emissions IEC 61000-3-2	Not applicable	
Voltage fluctuations/ flicker emissions IEC 61000-3-3	Not applicable	

Electromagnetic Immunity

Guidance and Manufacturer's Declaration - Electromagnetic Immunity - For All Equipment and Systems			
The Monarch Ceiling hoist is intended for use in the electromagnetic environment specified below.			
Immunity test	IEC 60601 test level	Compliance level	Electromagnetic environment - guidance
Electrostatic discharge (ESD) IEC 61000-4-2	+/-8 kV contact +/-15 kV air	+/-8 kV contact +/-15 kV air	Floors should be wood, concrete or ceramic tile. If floors are covered with synthetic material, the relative humidity should be at least 30%.
Surge IEC 61000-4-5	+/-1 kV differential mode +/-2 kV for common mode	+/-1 kV differential mode +/-2 kV for common mode	Mains power quality should be that of a typical commercial or hospital environment.
Power frequency (50/60 Hz) magnetic field IEC 61000-4-8	30 A/m	30 A/m	Power frequency magnetic fields should be at levels characteristic of a typical location in a typical commercial or hospital environment.
NOTE: <i>UT</i> is the AC mains voltage prior to application of the test level.			

Electromagnetic Immunity (continued)

Guidance and Manufacturer's Declaration - Electromagnetic Immunity - For All Equipment and Systems			
The Monarch Ceiling hoist is intended for use in the electromagnetic environment specified below.			
Immunity test	IEC 60601 test level	Compliance level	Electromagnetic environment - guidance
Radiated RF IEC 61000-4-3	10 V/m 80 MHz to 2.5 GHz, 1 KHz, 80% AM Mod.	10 V/m 80 MHz to 2.5 GHz, 1KHz, 80% AM Mod.	<p>Portable and mobile RF communications equipment should be used no closer to any part of the hoist, including cables, than the recommended separation distance calculated from the equation applicable to the frequency of the transmitter. Recommended separation distance:</p> $d = \left[\frac{3.5}{3} \right] \sqrt{P}$ $d = \left[\frac{3.5}{10} \right] \sqrt{P} \quad \text{80 MHz to 800 MHz}$ $d = \left[\frac{7}{10} \right] \sqrt{P} \quad \text{800 MHz to 2.5 GHz}$ <p>where P is the maximum output power rating of the transmitter in watts (W) according to the transmitter manufacturer and d is the recommended separation distance in metres.</p> <p>Field strengths from fixed RF transmitters, as determined by an electromagnetic site survey,^(a) should be less than the compliance level in each frequency range.^(b)</p> <p>Interference may occur in the vicinity of equipment marked with the following symbol:</p> 

Electromagnetic Immunity (continued)

NOTE 1: At 80 MHz and 800 MHz, the higher frequency applies.

NOTE 2: These guidelines may not apply in all situations. Electromagnetic propagation is affected by absorption and reflection from structures, objects and people.

(a) Field strengths from fixed transmitters, such as base stations for radio (cellular/cordless) telephones and land mobile radios, amateur radio, AM and FM broadcast and TV broadcast cannot be predicted theoretically with accuracy. To assess the electromagnetic environment due to fixed RF transmitters, an electromagnetic site survey should be considered. If the measured field strength in the location where the hoist is used exceeds the applicable RF compliance level above, the hoist should be observed to verify normal operation. If abnormal performance is observed, additional measures may be necessary, such as reorienting or relocating the hoist.

(b) Over the frequency range 150 kHz to 80 MHz, field strengths should be less than 3 V/m.

Recommended Separation Distance Between - Portable and Mobile RF Communications Equipment and the Ceiling hoist or Equipment and Systems that are not Life-Supporting

Recommended separation distances between portable and mobile RF communications equipment and the Monarch Ceiling hoist.

The Monarch Ceiling hoist is intended for use in electromagnetic environments in which radiated RF disturbances are controlled. The customer or the user of the hoist can help prevent electromagnetic interference by maintaining a minimum distance between portable and mobile RF communication equipment (transmitters) and the ceiling hoist as recommended below, according to the maximum output power of the communications

equipment.

**Rated maximum
output power of
transmitter W**

Separation distances according to frequency of transmitter m

150 kHz to 80 MHz

$$d = \left[\frac{3.5}{3} \right] \sqrt{P}$$

80 MHz to 800 MHz

$$d = \left[\frac{3.5}{10} \right] \sqrt{P}$$

800 MHz to 2.5 GHz

$$d = \left[\frac{7}{10} \right] \sqrt{P}$$

0.01

0.12

0.12

0.24

0.1

0.37

0.37

0.74

1

1.17

1.17

2.34

10

3.69

3.69

7.38

100

11.67

11.67

23.34

For transmitters rated at a maximum output power not listed above, the recommended separation distance d in metres (m) can be estimated using the equation applicable to the frequency of the transmitter, where P is the maximum output power rating of the transmitter in watts (W) according to the transmitter manufacturer.

NOTE 1: At 80 MHz and 800 MHz, the separation distance for the higher frequency range applies.

NOTE 2: These guidelines may not apply in all situations. Electromagnetic propagation is affected by absorption and reflection from structures, objects and people.

Authorised OpeMed Dealer

Monarch Portable Ceiling Hoist OWNER'S MANUAL

Part No. 01700130 / 1700133,
Document No. M920303 rev.001
© Copyright 2016

OpeMed (Europe) Ltd.
Clockhouse, Dogflud Way
Farnham, Surrey, GU9 7UD
www.OpeMed.net

For service or questions about this product, please contact your installing dealer.

DEALER NAME: _____

DEALER PHONE: _____